Growatt ShineLink

- Cable free, easy installation
- Automatic IP addressing, plug and play
- 120 meters long range, wide coverage
- Multiple inverters supported, up to 8
- Build-in storage, 1 month data
- Online monitoring and maintenance

POWER-ING TOMO-RROW

Growatt
powering tomorrow

www.ginverter.com

Datasheet	ShineLink

Communication Interface	
Rf433	Yes
Rf433(in free-field conditions)	Up to 120 m
Rf433(two walls blocking)	20 m

Power Supply	
Power consumption	<2W standby, <5W peak
AC power supply input voltage	196V~250V
AC power supply input frequency	50/60Hz

General Specifications	
Dimensions(L/H/W)mm	105/85/26mm
Weight	< 1kg
Mounting options	Tabletop/wall-mount
Degree of protection	IP30
Status display	LED
Ambient temperature range	-20 to 65 °C
Humidity	0-95% (non condensing)

Features	
Programmable dry contact	Opt
Graphical user interface	Android/IOS APP
Remote firmware upgrades	Yes
Max. number of devices to monitor	8(RF433)
Warranty	1 years

CE

GROWATT NEW ENERGY TECHNOLOGY Co.,LTD
T: + 86 755 2747 1900 F: + 86 755 2749 1460
A: No.28 Guangmming Road, Longteng Community, Shiyan, Baoan District, Shenzhen, P.R.China.
E: info@ginverter.com